

### Overview

### HP Engage One Prime I/O Hub



### Models

HP Engage One Prime I/O Hub

4VW60AA/AT

HP Engage One Prime White I/O Hub

4VW66AA/AT

### Service and Support

Rest easy that your IT investment is supported by a one-year standard limited warranty.

### Technical Specifications

<b>General</b>	<b>Ports</b>	<p>1 USB-C™ PD port dedicated for host platform (PD power source up to 15V/3A)</p> <p>1 USB-C™ PD port dedicated for peripheral (PD power source: 9V/3A, 5V/3A, 5V/0.9A)</p> <p>4 USB-A ports (USB 2.0)</p> <p>1 Powered USB port (12V) combined with 1 USB-A port (USB2.0)</p> <p>2 Powered RS232 ports (0/5/12V can be set in HP Engage One Prime OS setting menu)</p> <p>1 RJ12 port (24V/1A) for cash drawer</p> <p>1 RJ45 Ethernet port (10/100/1000)</p>
<b>LED Behavior</b>	<p><b>When host is connected</b></p> <p><b>When host is removed</b></p> <p><b>Power on without host</b></p> <p><b>When error occurs</b></p>	<p>On/off with host is on/off; breathing with host is breathing</p> <p>On for 15 seconds then breathing</p> <p>On for 15 seconds then breathing</p> <p>Blinking</p>
<b>Weight</b>		1.08lb (490g)
<b>Dimension</b>		55mm(W) x 220mm(L) x 26.4mm(H) (2.17inch x 8.66inch x 1.04inch)
<b>Power adaptor requirement</b>	<b>Rated power</b>	120W, 19.50V +/-5%, 6.15A(HP 4.5mm Barrel type)
<b>Temperature</b>	<p><b>Operating</b></p> <p><b>Non-operating</b></p>	<p>32~95 °F (0~35 °C)</p> <p>-22~149 °F (-30~+65 °C)</p>
<b>Relative humidity</b>	<b>Operating</b>	10%~90% RH,
<b>Altitude</b>	<p><b>Operating</b></p> <p><b>Non-operating</b></p>	<p>10000 ft. (3048 m)</p> <p>30000 ft. (9144 m)</p>
<b>Network manageability</b>	Wake On Lan (WoL) is not supported with HP Engage One Prime or HP Engage One Prime Plus	
<b>Power Delivery (PD)</b>	Support HP proprietary dynamic PD configuration when connecting with HP Engage One Prime or HP Engage One Prime Plus	
<b>Option Kit Contents</b>	HP Engage One Prime I/O Hub, Documentation	

### Summary of Changes

Date of change:	Version History:		Description of change:
	From v1 to v2		Warranty updated

© Copyright 2019 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.